



THE

user manual

Mark-II

rev. 29/03/2023

Per una più rapida comprensione e navigazione del manuale si suggerisce di leggerlo in formato digitale o di stamparlo a colori.

Tutti i fari Spotlight, a seconda della **sorgente LED** montata e della **potenza**, possono essere raggruppati in **6 famiglie** (rappresentate da **6 colori**).

LED Power	Powercon daisy chain	Cold start / Inrush current	Type	LED Source				
				White	Tunable White	RGBW	6C	8C
50W	Total load max 16A - 3,5KW	60A/230VAC	Fresnel PC Profile	1A Mark-II Firmware 1.01 DMX chart 1A				
85W			Downlight					
100W			Fresnel PC Profile					
200W			Fresnel PC Profile					
300W		80A/230VAC	Cyclorama			3 Mark-II Firmware 1.01 DMX chart 3	4 Mark-II Firmware 1.01 DMX chart 4	
700W		40A/230VAC	Fresnel PC Profile Followspot	1B Mark-II Firmware 1.03 DMX chart 1B	2 Mark-II Firmware 1.01 DMX chart 2			5 Mark-II Firmware 1.07 DMX chart 5

How to...	Settings	White 50-100-200	White 300-700	Tunable white	RGBW	6C	8C	Safety instructions	Logistics Weight & sizes
---------------------------	--------------------------	----------------------------------	-------------------------------	-------------------------------	----------------------	--------------------	--------------------	-------------------------------------	--

General info

In questa sezione vengono definiti i comandi con i quali controllare l'apparecchio e le priorità che hanno i comandi tra loro, in base alle impostazioni.

When switched on, the installed software version is displayed, followed by the display of the default settings, ie the currently set operating mode.

	White	White	TW	RGBW	6C	8C
If the luminaire is DMX controlled, after 3 seconds the display will show the mode and DMX address. Otherwise it will show the potentiometers status. By pressing the ENTER (or SETUP) button you access the SETTINGS . With the PREV and NEXT buttons you can scroll the items list which in case of value type entries will have the function of increasing (+) or decreasing (-) the values. The ENTER button allows to access the submenu and change the values which can be confirmed by pressing ENTER or canceled with the BACK button, which can be used also to exit the submenu and go back to the main menu.						
Display: - Banda rossa: la lista di preset su cui stiamo lavorando. Sono 3: o MANUAL PRESET : LEE filters + selezione di CCT o MANUAL COLOUR : selezione LEE filters o MANUAL CCT : CCT (1500K – 20000K) Per spostarsi da una lista di preset all'altra usare le frecce - Nome del filtro + codice filtro - Temperatura in Kelvin del CCT - Valore del dimmer 0 – 100% - Valore del dimmer 0 – 255 All'accensione il faro richiama l'ultimo valore di dimmer e preset salvati. Come salvare un preset: 1. selezionare i valori di dimmer e preset desiderati 2. tenere premuto l'encoder rosso (CCT/COLOUR WHEEL) per 3 secondi 3. l'avvenuto salvataggio sarà confermato dal colore rosso delle scritte Nota: - se cambio il dimmer il colore passa da rosso a giallo (e quando torno sul valore salvato torna rosso) - se cambio il preset il colore passa da rosso a bianco Se il faro è collegato ad una consolle DMX, gli encoder vengono disabilitati in automatico. Se si ha la necessità di attivare gli encoder senza scollegare il faro dalla consolle, tenere premuto per 2 secondi il primo pulsante dall'alto. Per uscire da questa modalità basta tenere premuto per 2 secondi lo stesso pulsante.						

All the luminaires are designed to be used in different operating modes:

- LOCAL ENCODER
- DMX
- [RDM](#)
- [STAND ALONE](#) (only for RGBW, 6C, 8C)

Input priority is given:

- in absence of the DMX signal the value set with the potentiometer will be active
- when there is the DMX signal the relevant signal is followed and the potentiometer will be ignored
- if the DMX signal is eliminated or lost, the DMX set level is kept until you act on the potentiometer, which will set the new value

All the fixtures are equipped with a temperature control of the LED and of the driver motherboard, which, to avoid an early deterioration in case of overtemperature, regulates the light intensity.

Some parameters can be modified directly into the fixture by using the [SETTINGS](#) menu or by using a console thanks to the DMX PERSONALITIES and related channels.

How to...	Settings	White 50-100-200	White 300-700	Tunable white	RGBW	6C	8C	Safety instructions	Logistics Weight & sizes
---------------------------	--------------------------	----------------------------------	-------------------------------	-------------------------------	----------------------	--------------------	--------------------	-------------------------------------	--

Settings

In questa sezione vengono elencate le singole voci del menu o funzioni evidenziando, per ognuna di esse, a quali famiglie di apparecchi sono applicabili.

		Values	White 50-200	White 300-700	Tunable White	RGBW	6C	8C	How to...
DMX SETTINGS	DMX ADDRESS	1 (default) - ... - xxx	YES	YES	YES	YES	YES	YES	How to set the DMX address and DMX personality
	DMX PERSONALITY	See related table	DMX chart 1A	DMX chart 1B	DMX chart 2	DMX chart 3	DMX chart 4	DMX chart 5	
	WIRELESS DMX	ON OFF (default)	YES	YES	YES	-	YES	YES	
	SHoW ID	24100 - ... - 24300 (default) - ... - 24359	YES	YES	YES	-	YES	YES	
STAND ALONE	SHoW KEY	000 (default) - ... - 500	YES	YES	YES	-	YES	YES	
	STAND ALONE	DISABLED (default) STDALONE MANUAL STDALONE AUTO SCENE MASTER MANUAL MASTER AUTO SCENE SLAVE	-	-	-	YES	YES	YES	How to set the stand alone function
	MANUAL MODE								
	AUTO SCENE MODE								
	CUSTOM PRESETS								
OPTIONS	LED DELAY	OFF - 50 - ... - 1000 (default) - ... - 2000ms	YES	YES	YES	YES	YES	YES	How to emulate the performance of halogen lamp
	DIMMING CURVE	LINEAR (1) HALO (2) QUADRATIC (default) (3) GAMMA 2.6 (4) GAMMA 2.8 (5) S (6)	YES	YES	YES	YES 1-2-3	YES	YES	
	AMBER SHIFT	ON OFF (default)	-	-	-	-	YES	YES	
	OUTPUT FREQUENCY	500 - 501 - ... - 1200 (default) - ... - 20000 Hz	YES	YES	YES	YES	YES	YES	How to remove flickering
	LED BOOST	ON OFF (default)	YES	-	YES	YES	YES	YES	How to increase +20% light output
	FAN MODE	AUTO (default) STANDARD SILENT	YES	YES	YES	YES	YES	YES	How to set the silent mode
	DISPLAY ROTATION	STANDARD (default) ROTATED	YES	YES	YES	YES	YES	YES	How to set the display
	DISPLAY ON/OFF	ON (default) OFF	YES	YES	YES	YES	YES	YES	
	MANUAL CONTROL	ON (default) OFF	YES	YES	YES	-	YES	YES	Abilita/disabilita il funzionamento degli encoder
	LED CALIBRATION	RED GREEN BLU WHITE AMBER CYAN LIME	- - - - - - -	- - - - - - -	- - - - - - -	YES YES YES YES -	YES YES YES YES -	YES YES YES -	How to set LED calibration
INFO	DEFAULT SET		YES	YES	YES	YES	YES	YES	
	FACTORY SETTINGS		YES	YES	YES	YES	YES	YES	
	LED TEMPERATURE	°C	YES	YES	YES	YES	YES	YES	
	BOARD TEMPERATURE		YES	YES	YES	-	YES	YES	
	CHIP TEMPEARURE		-	YES	YES	-	YES	YES	
	LED TIME		YES	YES	-	-	-	-	
	RED LED TIME	hr - min	-	-	-	YES	YES	YES	
	GREEN LED TIME	hr - min	-	-	-	YES	YES	YES	
	BLU LED TIME	hr - min	-	-	-	YES	YES	YES	
	WHITE LED TIME	hr - min	-	-	-	YES	-	-	
	AMBER LED TIME	hr - min	-	-	-	-	YES	YES	
	CYAN LED TIME	hr - min	-	-	-	-	YES	YES	
	LIME LED TIME	hr - min	-	-	-	-	YES	YES	
	WARM WHITE TIME	hr - min	-	-	YES	-	-	YES	
	COLD WHITE TIME	hr - min	-	-	YES	-	-	YES	
	UNIT TIME	hr - min	YES	YES	YES	YES	YES	YES	
	SOFTWARE VERSION	V. Release date	YES	YES	YES	YES	YES	YES	

DEFAULT SETTINGS: It brings the parameters back to the "original built-in settings" (i.e. fan speed, dimming curve, delay...) as they came out from factory

FACTORY SETTINGS: Password-protected menu, used by Spotlight Tech. Dept to apply special settings (limit the current, working hours reset, limit the power consumption, ...). These parameters do NOT affect the "default settings" NOTE: Not for final users

How to...	Settings	White 50-100-200	White 300-700	Tunable white	RGBW	6C	8C	Safety instructions	Logistics Weight & sizes
---------------------------	--------------------------	----------------------------------	-------------------------------	-------------------------------	----------------------	--------------------	--------------------	-------------------------------------	--

DMX Personalities

Nelle sezioni successive vengono presentate le **Personalities**, ovvero le **DMX chart** disponibili per ciascun gruppo per consentire all'operatore di scegliere in quale modalità far funzionare il faro in base ai parametri che si decide di controllare e al numero di canali disponibili sulla console che si sta utilizzando.

WHITE 50-100-200W

1CH			
8 bit	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)

2CH			
8 bit	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)
2 ch	STROBO	0..1.255	OFF from slow (3,86 s) to fast (30 ms)

3CH			
16 bit	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)
2 ch	DIMMER FINE	0..255	from OFF (0) to full (255)
3 ch	STROBO	0..1.255	OFF from slow (3,86 s) to fast (30 ms)

CURRENT MODULATION - Si tratta di una modalità di funzionamento per eliminare i disturbi di flickering, causati dal pilotaggio in PWM del LED, e i disturbi acustici, generati dai componenti elettronici.

Questa modalità è specificatamente indicata per applicazioni in studi TV o in camere acustiche dove è richiesta la massima silenziosità degli apparecchi l'assenza di flicker.

WHITE 300-700W

1CH			
8 bit	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)

3CH			
8 bit	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)
2 ch	STROBO & STORE	See related table	
3 ch	SERVICE	0..255	See related table

6CH			
16 bit	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)
2 ch	DIMMER FINE	0..255	from OFF (0) to full (255)
3 ch	DELAY	See related table	
4 ch	FAN	0..255	from minimum to maximum
5 ch	STROBO & STORE	See related table	
6 ch	SERVICE	See related table	

How to...	Settings	White 50-100-200	White 300-700	Tunable white	RGBW	6C	8C	Safey instructions	Logistics Weight & sizes
---------------------------	--------------------------	----------------------------------	-------------------------------	-------------------------------	----------------------	--------------------	--------------------	------------------------------------	--

TUNABLE WHITE

EASY			
8 bit	Function	DMX value	Description
1 ch	DIMMER	0.255	from OFF (0) to full (255)
2 ch	CCT LINEAR	See related table	

SPLIT			
8 bit	Function	DMX value	Description
1 ch	DIMMER	0.255	GM - GENERAL MASTER
2 ch	WARM WHITE	0.255	from OFF (0) to full (255)
3 ch	COLD WHITE	0.255	from OFF (0) to full (255)
4 ch	STROBO & STORE	See related table	
5 ch	SERVICE	See related table	

STUDIO			
16 bit	Function	DMX value	Description
1 ch	DIMMER	0.255	from OFF (0) to full (255)
2 ch	DIMMER FINE	0.255	from OFF (0) to full (255)
3 ch	CCT PRESET	See related table	
4 ch	WW +/- correzione live del CCT STEP selezionato (= "zero point")	0..15 6..111 112..144 145..239 240..255	OFF from minimum to standard CCT STEP from standard to maximum OFF
5 ch	CW +/- correzione live del CCT STEP selezionato (= "zero point")	0..15 6..111 112..144 145..239 240..255	OFF from minimum to standard CCT STEP from standard to maximum OFF
6 ch	DELAY	See related table	
7 ch	FAN	0.255	from minimum to maximum
8 ch	STROBO & STORE	See related table	
9 ch	SERVICE	See related table	

SPLIT			
16 bit	Function	DMX value	Description
1 ch	DIMMER	0.255	from OFF (0) to full (255)
2 ch	DIMMER FINE	0.255	from OFF (0) to full (255)
3 ch	WARM WHITE	0.255	from OFF (0) to full (255)
4 ch	WARM WHITE FINE	0.255	from OFF (0) to full (255)
5 ch	COLD WHITE	0.255	from OFF (0) to full (255)
6 ch	COLD WHITE FINE	0.255	from OFF (0) to full (255)
7 ch	DELAY	See related table	
8 ch	FAN	0.255	from minimum to maximum
9 ch	STROBO & STORE	See related table	
10 ch	SERVICE	See related table	

THEATRE FULL			
16 bit	Function	DMX value	Description
1 ch	DIMMER	0.255	from OFF (0) to full (255)
2 ch	DIMMER FINE	0.255	from OFF (0) to full (255)
3 ch	CCT LINEAR	See related table	
4 ch	DELAY	See related table	
5 ch	FAN	0.255	from minimum to maximum
6 ch	STROBO & STORE	See related table	
7 ch	SERVICE	See related table	

How to...	Settings	White 50-100-200	White 300-700	Tunable white	RGBW	6C	8C	Safety instructions	Logistics Weight & sizes
---------------------------	--------------------------	----------------------------------	-------------------------------	-------------------------------	----------------------	--------------------	--------------------	-------------------------------------	--

RGBW

EASY			
8 bit	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)
2 ch	CCT PRESET	See related table	
3 ch	COLOUR PRESET	See related table	

Note: CCT PRESET has priority over COLOUR PRESET

HSI			
8 bit	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)
2 ch	HUE	0..255	Sequence: R, R+G, G, G+B, B, B+R, R
3 ch	HUE FINE	0..255	Selection of the colour - fine
4 ch	SATURATION	0..255	Color saturation - from the HUE preset towards the choosen white in the CCT Color Point (COLOR POINT CCT - ALWAYS ACTIVE)
6 ch	STROBO & STORE	See related table	
7 ch	SERVICE	See related table	

CMY			
8 bit	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)
2 ch	CYAN	0..255	from OFF (0) to full (255)
3 ch	MAGENTA	0..255	from OFF (0) to full (255)
4 ch	YELLOW	0..255	from OFF (0) to full (255)
5 ch	STROBO & STORE	See related table	
6 ch	SERVICE	See related table	

RGBW			
8 bit	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)
2 ch	RED	0..255	from OFF (0) to full (255)
3 ch	GREEN	0..255	from OFF (0) to full (255)
4 ch	BLUE	0..255	from OFF (0) to full (255)
5 ch	WHITE	0..255	from OFF (0) to full (255)
6 ch	CCT PRESET	See related table	
7 ch	COLOUR PRESET	See related table	
8 ch	STROBO & STORE	See related table	
9 ch	SERVICE	See related table	

FULL			
16 bit	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)
2 ch	DIMMER FINE	0..255	from OFF (0) to full (255)
3 ch	RED	0..255	from OFF (0) to full (255)
4 ch	RED FINE	0..255	from OFF (0) to full (255)
5 ch	GREEN	0..255	from OFF (0) to full (255)
6 ch	GREEN FINE	0..255	from OFF (0) to full (255)
7 ch	BLUE	0..255	
8 ch	BLUE FINE	0..255	
9 ch	WHITE	0..255	
10 ch	WHITE FINE	0..255	
11 ch	COLOUR PRESET	See related table	
12 ch	CCT PRESET	See related table	
13 ch	DELAY	See related table	
14 ch	FAN	0..255	from minimum to maximum
15 ch	STROBO & STORE	See related table	
16 ch	SERVICE	See related table	

How to...	Settings	White 50-100-200	White 300-700	Tunable white	RGBW	6C	8C	Safety instructions	Logistics Weight & sizes
---------------------------	--------------------------	----------------------------------	-------------------------------	-------------------------------	----------------------	--------------------	--------------------	-------------------------------------	--

6 COLOURS

8 bit	EASY		
	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)
2 ch	ROSCO FILTERS	See related table	
3 ch	LEE FILTERS	See related table	
4 ch	CCT PRESET	See related table	

Note: CCT PRESET has priority over COLOUR PRESET

8 bit	HSIC		
	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)
2 ch	HUE	0..255	Sequence: R, R+L, R+G+L, G+L, G, G+C, G+B+C, B+C, B, B+A, R+B+A, R+A, R
3 ch	HUE FINE	0..255	Selection of the colour - fine
4 ch	SATURATION (to dim the channel of CCT LINEAR)	0..255	
5 ch	CCT LINEAR	See related table	
6 ch	STROBO & STORE	See related table	
7 ch	SERVICE	See related table	

8 bit	RGBACL		
	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)
2 ch	RED	0..255	from OFF (0) to full (255)
3 ch	GREEN	0..255	from OFF (0) to full (255)
4 ch	BLUE	0..255	from OFF (0) to full (255)
5 ch	AMBER	0..255	from OFF (0) to full (255)
6 ch	CYAN	0..255	from OFF (0) to full (255)
7 ch	LIME	0..255	from OFF (0) to full (255)
8 ch	STROBO & STORE	See related table	
9 ch	SERVICE	See related table	

16 bit	STUDIO		
	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)
2 ch	DIMMER FINE	0..255	from OFF (0) to full (255)
3 ch	RED	0..255	from OFF (0) to full (255)
4 ch	RED FINE	0..255	from OFF (0) to full (255)
5 ch	GREEN	0..255	from OFF (0) to full (255)
6 ch	GREEN FINE	0..255	from OFF (0) to full (255)
7 ch	BLUE	0..255	from OFF (0) to full (255)
8 ch	BLUE FINE	0..255	from OFF (0) to full (255)
9 ch	AMBER	0..255	from OFF (0) to full (255)
10 ch	AMBER FINE	0..255	from OFF (0) to full (255)
11 ch	CYAN	0..255	from OFF (0) to full (255)
12 ch	CYAN FINE	0..255	from OFF (0) to full (255)
13 ch	LIME	0..255	from OFF (0) to full (255)
14 ch	LIME FINE	0..255	from OFF (0) to full (255)
15 ch	ROSCO FILTERS	See related table	
16 ch	LEE FILTERS	See related table	
17 ch	CCT STEPS	See related table	
18 ch	GREEN +/-	0..15 16..126 127..144 145..255	OFF MINUS GREEN - ZERO POINT-CENTER PLUS GREEN +
19 ch	DELAY	See related table	
20 ch	FAN	0..255	from minimum to maximum
21 ch	STROBO & STORE	See related table	
22 ch	SERVICE	See related table	
23 ch	FREE 1		
24ch	FREE 2		

How to...	Settings	White 50-100-200	White 300-700	Tunable white	RGBW	6C	8C	Safety instructions	Logistics Weight & sizes
---------------------------	--------------------------	----------------------------------	-------------------------------	-------------------------------	----------------------	--------------------	--------------------	-------------------------------------	--

16 bit	THEATRE		
	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)
2 ch	DIMMER FINE	0..255	from OFF (0) to full (255)
3 ch	RED	0..255	from OFF (0) to full (255)
4 ch	RED FINE	0..255	from OFF (0) to full (255)
5 ch	GREEN	0..255	from OFF (0) to full (255)
6 ch	GREEN FINE	0..255	from OFF (0) to full (255)
7 ch	BLUE	0..255	from OFF (0) to full (255)
8 ch	BLUE FINE	0..255	from OFF (0) to full (255)
9 ch	AMBER	0..255	from OFF (0) to full (255)
10 ch	AMBER FINE	0..255	from OFF (0) to full (255)
11 ch	CYAN	0..255	from OFF (0) to full (255)
12 ch	CYAN FINE	0..255	from OFF (0) to full (255)
13 ch	LIME	0..255	from OFF (0) to full (255)
14 ch	LIME FINE	0..255	from OFF (0) to full (255)
15 ch	ROSCO FILTERS	See related table	
16 ch	LEE FILTERS	See related table	
17 ch	SATURATION (to dim the channel of CCT LINEAR)	0..255	from OFF (0) to full (255)
18 ch	CCT LINEAR	See related table	
19 ch	GREEN +/-	0..15 16..126 127..144 145..255	OFF MINUS GREEN - ZERO POINT - CENTER PLUS GREEN +
20 ch	DELAY	See related table	
21 ch	FAN	0..255	from minimum to maximum
22 ch	STROBO & STORE	See related table	
23 ch	SERVICE	See related table	
24 ch	FREE 1		
25 ch	FREE 2		

Note: CCT LINEAR has priority over COLOUR PRESET has priority over manual selected colours (from channel 3 to 14)

16 bit	RGBACL		
	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)
2 ch	DIMMER FINE	0..255	from OFF (0) to full (255)
3 ch	RED	0..255	from OFF (0) to full (255)
4 ch	RED FINE	0..255	from OFF (0) to full (255)
5 ch	GREEN	0..255	from OFF (0) to full (255)
6 ch	GREEN FINE	0..255	from OFF (0) to full (255)
7 ch	BLUE	0..255	from OFF (0) to full (255)
8 ch	BLUE FINE	0..255	from OFF (0) to full (255)
9 ch	AMBER	0..255	from OFF (0) to full (255)
10 ch	AMBER FINE	0..255	from OFF (0) to full (255)
11 ch	CYAN	0..255	from OFF (0) to full (255)
12 ch	CYAN FINE	0..255	from OFF (0) to full (255)
13 ch	LIME	0..255	from OFF (0) to full (255)
14 ch	LIME FINE	0..255	from OFF (0) to full (255)

How to...	Settings	White 50-100-200	White 300-700	Tunable white	RGBW	6C	8C	Safety instructions	Logistics Weight & sizes
---------------------------	--------------------------	----------------------------------	-------------------------------	-------------------------------	----------------------	--------------------	--------------------	-------------------------------------	--

8 COLOURS

8 bit	EASY		
	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)
2 ch	ROSCO FILTERS	See related table	
3 ch	LEE FILTERS	See related table	
4 ch	CCT PRESET	See related table	

Note: CCT PRESET has priority over COLOUR PRESET

8 bit	HSIC		
	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)
2 ch	HUE	0..255	Sequence: R, R+L, R+G+L, G+L, G, G+C, G+B+C, B+C, B, B+A, R+B+A, R+A, R
3 ch	HUE FINE	0..255	Selection of the colour - fine
4 ch	SATURATION (to dim the channel of CCT LINEAR)	0..255	
5 ch	CCT LINEAR	See related table	
6 ch	STROBO & STORE	See related table	
7 ch	SERVICE	See related table	

8 bit	RGBACL+WW+CW		
	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)
2 ch	RED	0..255	from OFF (0) to full (255)
3 ch	GREEN	0..255	from OFF (0) to full (255)
4 ch	BLUE	0..255	from OFF (0) to full (255)
5 ch	AMBER	0..255	from OFF (0) to full (255)
6 ch	CYAN	0..255	from OFF (0) to full (255)
7 ch	LIME	0..255	from OFF (0) to full (255)
8 ch	WARM WHITE	0..255	from OFF (0) to full (255)
9 ch	COLD WHITE	0..255	from OFF (0) to full (255)
10 ch	STROBO & STORE	See related table	
11 ch	SERVICE	See related table	

16 bit	RGBACL+WW+CW		
	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)
2 ch	DIMMER FINE	0..255	from OFF (0) to full (255)
3 ch	RED	0..255	from OFF (0) to full (255)
4 ch	RED FINE	0..255	from OFF (0) to full (255)
5 ch	GREEN	0..255	from OFF (0) to full (255)
6 ch	GREEN FINE	0..255	from OFF (0) to full (255)
7 ch	BLUE	0..255	from OFF (0) to full (255)
8 ch	BLUE FINE	0..255	from OFF (0) to full (255)
9 ch	AMBER	0..255	from OFF (0) to full (255)
10 ch	AMBER FINE	0..255	from OFF (0) to full (255)
11 ch	CYAN	0..255	from OFF (0) to full (255)
12 ch	CYAN FINE	0..255	from OFF (0) to full (255)
13 ch	LIME	0..255	from OFF (0) to full (255)
14 ch	LIME FINE	0..255	from OFF (0) to full (255)
15 ch	WARM WHITE	0..255	from OFF (0) to full (255)
16 ch	WARM WHITE FINE	0..255	from OFF (0) to full (255)
17 ch	COLD WHITE	0..255	from OFF (0) to full (255)
18 ch	COLD WHITE FINE	0..255	from OFF (0) to full (255)

How to...	Settings	White 50-100-200	White 300-700	Tunable white	RGBW	6C	8C	Safety instructions	Logistics Weight & sizes
---------------------------	--------------------------	----------------------------------	-------------------------------	-------------------------------	----------------------	--------------------	--------------------	-------------------------------------	--

16 bit	STUDIO		
	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)
2 ch	DIMMER FINE	0..255	from OFF (0) to full (255)
3 ch	RED	0..255	from OFF (0) to full (255)
4 ch	RED FINE	0..255	from OFF (0) to full (255)
5 ch	GREEN	0..255	from OFF (0) to full (255)
6 ch	GREEN FINE	0..255	from OFF (0) to full (255)
7 ch	BLUE	0..255	from OFF (0) to full (255)
8 ch	BLUE FINE	0..255	from OFF (0) to full (255)
9 ch	AMBER	0..255	from OFF (0) to full (255)
10 ch	AMBER FINE	0..255	from OFF (0) to full (255)
11 ch	CYAN	0..255	from OFF (0) to full (255)
12 ch	CYAN FINE	0..255	from OFF (0) to full (255)
13 ch	LIME	0..255	from OFF (0) to full (255)
14 ch	LIME FINE	0..255	from OFF (0) to full (255)
15 ch	WARM WHITE	0..255	from OFF (0) to full (255)
16 ch	WARM WHITE FINE	0..255	from OFF (0) to full (255)
17 ch	COLD WHITE	0..255	from OFF (0) to full (255)
18 ch	COLD WHITE FINE	0..255	from OFF (0) to full (255)
19 ch	ROSCO FILTERS	See related table	
20 ch	LEE FILTERS	See related table	
21 ch	CCT STEPS	See related table	
22 ch	GREEN +/-	0..15 16..126 127..144 145..255	OFF MINUS GREEN - ZERO POINT - CENTER PLUS GREEN +
23 ch	DELAY	See related table	
24 ch	FAN	0..255	from minimum to maximum
25 ch	STROBO & STORE	See related table	
26 ch	SERVICE	See related table	
27 ch	FREE 1		
28 ch	FREE 2		

16 bit	THEATRE		
	Function	DMX value	Description
1 ch	DIMMER	0..255	from OFF (0) to full (255)
2 ch	DIMMER FINE	0..255	from OFF (0) to full (255)
3 ch	RED	0..255	from OFF (0) to full (255)
4 ch	RED FINE	0..255	from OFF (0) to full (255)
5 ch	GREEN	0..255	from OFF (0) to full (255)
6 ch	GREEN FINE	0..255	from OFF (0) to full (255)
7 ch	BLUE	0..255	from OFF (0) to full (255)
8 ch	BLUE FINE	0..255	from OFF (0) to full (255)
9 ch	AMBER	0..255	from OFF (0) to full (255)
10 ch	AMBER FINE	0..255	from OFF (0) to full (255)
11 ch	CYAN	0..255	from OFF (0) to full (255)
12 ch	CYAN FINE	0..255	from OFF (0) to full (255)
13 ch	LIME	0..255	from OFF (0) to full (255)
14 ch	LIME FINE	0..255	from OFF (0) to full (255)
15 ch	WARM WHITE	0..255	from OFF (0) to full (255)
16 ch	WARM WHITE FINE	0..255	from OFF (0) to full (255)
17 ch	COLD WHITE	0..255	from OFF (0) to full (255)
18 ch	COLD WHITE FINE	0..255	from OFF (0) to full (255)
19 ch	ROSCO FILTERS	See related table	
20 ch	LEE FILTERS	See related table	
21 ch	SATURATION (to dim the channel of CCT LINEAR)	0..255	from OFF (0) to full (255)
22 ch	CCT LINEAR	See related table	
23 ch	GREEN +/-	0..15 16..126 127..144 145..255	OFF MINUS GREEN - ZERO POINT - CENTER PLUS GREEN +
24 ch	DELAY	See related table	
25 ch	FAN	0..255	from minimum to maximum
26 ch	STROBO & STORE	See related table	
27 ch	SERVICE	See related table	
28 ch	FREE 1		
29 ch	FREE 2		

Note: CCT LINEAR has priority over COLOUR PRESET has priority over manual selected colours (from channel 3 to 14)

How to...	Settings	White 50-100-200	White 300-700	Tunable white	RGBW	6C	8C	Safety instructions	Logistics Weight & sizes
---------------------------	--------------------------	----------------------------------	-------------------------------	-------------------------------	----------------------	--------------------	--------------------	-------------------------------------	--

Related tables

SERVICE CHANNEL

Permette di modificare tutte le impostazioni da remoto (console) che normalmente si impostano manualmente dal menu STAND ALONE and OPTIONS del faro

					White	White	TW	RGBW	6C	8C
SERVICE 1 (RGBW, 6C, 8C)	STAND ALONE (here you create)	CUSTOM PRESETS	0..5 6..18 19..31 32..44 45..57 58..70 71..83 84..96 97..109 110..122 123..135 136..148 149..161 162..174 175..187 188..200 201..213 214..226 227..239 240..255	OFF CUSTOM PRESET 1 CUSTOM PRESET 2 CUSTOM PRESET 3 CUSTOM PRESET 4 CUSTOM PRESET 5 CUSTOM PRESET 6 CUSTOM PRESET 7 CUSTOM PRESET 8 CUSTOM PRESET 9 CUSTOM PRESET 10 CUSTOM PRESET 11 CUSTOM PRESET 12 CUSTOM PRESET 13 CUSTOM PRESET 14 CUSTOM PRESET 15 CUSTOM PRESET 16 CUSTOM PRESET 17 CUSTOM PRESET 18 CUSTOM PRESET 19	-	-	-	YES	YES	YES
SERIVCE (White, TW) or SERVICE 2 (RGBW, 6C, 8C)	OPTIONS (here you set)	LED DELAY	0..5	INACTIVE 6..11 12..17 18..23 24..29 30..35 36..41 42..47 48..53 54..59 60..65 66..71	OFF 50 ms 100 ms 240 ms 400 ms 600 ms 800 ms 1000 ms (default) 1200 ms 1600 ms 2000 ms	-	YES	YES	YES	YES
		DIMMING CURVE	72..77 78..81 82..83 84..85 86..87 88..89	LINEAR QUADRATIC S HALO (default) GAMMA 2.6 GAMMA 2.8	-	YES	YES	YES	YES	YES
		OUTPUT FREQUENCY	90..95 96..101 102..107 108..113 114..119 120..125 126..131 132..137 138..143	600 Hz 900 Hz 1200 Hz (default) 2100 Hz 4200 Hz 6000 Hz 10200 Hz 15600 Hz 19800 Hz	-	YES	YES	YES	YES	YES
		LED BOOST	144..149 150..155	ON OFF (default)	-	YES	YES	YES	YES	YES
		FAN MODE	156..161 162..167 168..173	AUTO (default) STANDARD SILENT	-	YES	YES	YES	YES	YES
		DISPLAY ROTATION DISPLAY ON/FF	174..179 180..185 186..191 192..197	STANDARD (default) ROTATED OFF ON (default)	-	YES	YES	YES	YES	YES
		LED CALIBRATION	198..203	COLOUR CALIBRATION (for all) NO FUNCTION (for White 300-700)	-	YES	YES	YES	YES	YES
		DEFAULT SETTINGS (for future use)	204..209 210..255	DEFAULT SETTINGS FREE	-	YES	YES	YES	YES	YES

STROBE & STORE CHANNEL

					White	White	TW	RGBW	6C	8C
STROBE & STORE	STROBE	0 1..150 151..200	OFF from slow (3.86 s) to fast (30 ms) OFF	-	YES	YES	YES	YES	YES	YES
	STORE 1 (here you save what you created in SERVICE 1)	201..210 211..230	Once created the desired CUSTOM PRESET, keep on hold for 5 seconds to store the new value. OFF	-	-	-	YES	YES	YES	YES
	STORE 2 (here you save what you set in SERVICE / SERVICE 2)	231..240 241..255	Once set the desired OPTION, keep on hold for 5 seconds to store the new value. OFF	-	YES	YES	YES	YES	YES	YES

How to...	Settings	White 50-100-200	White 300-700	Tunable white	RGBW	6C	8C	Safety instructions	Logistics Weight & sizes
---------------------------	--------------------------	----------------------------------	-------------------------------	-------------------------------	----------------------	--------------------	--------------------	-------------------------------------	--

CCT CHANNEL

	TW		RGBW	6C			8C		
	LINEAR	PRESET	PRESET	LINEAR	STEP	PRESET	LINEAR	STEP	PRESET
NONE	-	-	0..15	-	0..4	0..4	-	0..4	0..4
1500K	-	-	-	0..0..	5..7..	5..11..	0..0..	5..7..	5..11..
1500K-1600K	-	-	-	1..7..	8..11..	-	1..7..	8..11..	-
1600K	-	-	-	8..8..	12..14..	12..18..	8..8..	12..14..	12..18..
1600K-1700K	-	-	-	9..15..	15..18..	-	9..15..	15..18..	-
1700K	-	-	-	16..16..	19..21..	19..25..	16..16..	19..21..	19..25..
1700K-1800K	-	-	-	17..23..	22..25..	-	17..23..	22..25..	-
1800K	-	-	-	24..24..	26..28..	26..32..	24..24..	26..28..	26..32..
1800K-1900K	-	-	-	25..31..	29..32..	-	25..31..	29..32..	-
1900K	-	-	-	32..32..	33..35..	33..39..	32..32..	33..35..	33..39..
1900K-2000K	-	-	-	33..39..	36..39..	-	33..39..	36..39..	-
2000K	-	-	-	40..40..	40..42..	40..46..	40..40..	40..42..	40..46..
2000K-2100K	-	-	-	41..47..	43..46..	-	41..47..	43..46..	-
2100K	-	-	-	48..48..	47..49..	47..53..	48..48..	47..49..	47..53..
2100K-2200K	-	-	-	49..55..	50..53..	-	49..55..	50..53..	-
2200K	-	-	-	56..56..	54..56..	54..60..	56..56..	54..56..	54..60..
2200K-2300K	-	-	-	57..63..	57..60..	-	57..63..	57..60..	-
2300K	-	-	-	64..64..	61..63..	61..67..	64..64..	61..63..	61..67..
2300K-2400K	-	-	-	65..71..	64..67..	-	65..71..	64..67..	-
2400K	-	-	-	72..72..	68..70..	68..74..	72..72..	68..70..	68..74..
2400K-2500K	-	-	-	73..79..	71..74..	-	73..79..	71..74..	-
2500K	-	-	-	80..80..	75..77..	75..81..	80..80..	75..77..	75..81..
2500K-2600K	-	-	-	81..86..	78..81..	-	81..86..	78..81..	-
2600K	-	-	-	87..87..	82..84..	82..88..	87..87..	82..84..	82..88..
2600K-2700K	-	-	-	88..93..	85..88..	-	88..93..	85..88..	-
2700K	0	0..35..	16..45..	94..94..	89..91..	89..95..	94..94..	89..91..	89..95..
2700K-3000K	2700K-2800K	1..41..	-	95..100..	92..95..	-	95..100..	92..95..	-
	2800K			101..101..	96..98..	96..102..	101..101..	96..98..	96..102..
	2800K-2900K			102..107..	99..102..	-	102..107..	99..102..	-
	2900K			108..108..	103..105..	103..109..	108..108..	103..105..	103..109..
	2900K-3000K			109..114..	106..109..	-	109..114..	106..109..	-
3000K	42	36..70..	46..75..	115..115..	110..112..	110..116..	115..115..	110..112..	110..116..
3000K-3200K	3000K-3100K	43..83..	-	116..121..	113..116..	-	116..121..	113..116..	-
	3100K			122..122..	117..119..	117..123..	122..122..	117..119..	117..123..
	3100K-3200K			123..128..	120..123..	-	123..128..	120..123..	-
3200K (default)	84	71..105..	76..105..	129..129..	124..126..	124..130..	129..129..	124..126..	124..130..
3200K-3500K	3200K-3300K	85..125..	-	130..135..	127..130..	-	130..135..	127..130..	-
	3300K			136..136..	131..133..	131..137..	136..136..	131..133..	131..137..
	3300K-3400K			137..142..	134..137..	-	137..142..	134..137..	-
	3400K			143..143..	138..140..	138..144..	143..143..	138..140..	138..144..
	3400K-3500K			144..149..	141..144..	-	144..149..	141..144..	-
3500K	126	106..140..	106..135..	150..150..	145..147..	145..151..	150..150..	145..147..	145..151..
3500K-4000K	127..168..	-	-	151..156..	148..151..	-	151..156..	148..151..	-
4000K	169	141..175..	136..165..	157..157..	152..154..	152..158..	157..157..	152..154..	152..158..
4000K-5600K	4000K-5000K	170..211..	-	158..163..	155..158..	-	158..163..	155..158..	-
	5000K			164..164..	159..161..	159..165..	164..164..	159..161..	159..165..
	5000K-5600K			165..170..	162..165..	-	165..170..	162..165..	-
5600K	212	176..210..	166..195..	171..171..	166..168..	166..172..	171..171..	166..168..	166..172..
5600K-6500K	5600K-6000K	213..254..	-	172..177..	169..172..	-	172..177..	169..172..	-
	6000K			178..178..	173..175..	173..179..	178..178..	173..175..	173..179..
	6000K-6500K			179..184..	176..179..	-	179..184..	176..179..	-
6500K	255	211..225..	196..225..	185..185..	180..182..	180..186..	185..185..	180..182..	180..186..
6500K-8000K	-	-	-	186..191..	183..186..	-	186..191..	183..186..	-
8000K	-	-	-	192..192..	187..189..	187..193..	192..192..	187..189..	187..193..
8000K-10000K	-	-	-	193..198..	190..193..	-	193..198..	190..193..	-
10000K	-	-	-	199..199..	194..196..	194..200..	199..199..	194..196..	194..200..
10000K-12000K	-	-	-	200..205..	197..200..	-	200..205..	197..200..	-
12000K	-	-	-	206..206..	201..203..	201..207..	206..206..	201..203..	201..207..
12000K-14000K	-	-	-	207..212..	204..207..	-	207..212..	204..207..	-
14000K	-	-	-	213..213..	208..210..	208..214..	213..213..	208..210..	208..214..
14000K-15000K	-	-	-	214..219..	211..214..	-	214..219..	211..214..	-
15000K	-	-	-	220..220..	215..217..	215..221..	220..220..	215..217..	215..221..
15000K-16000K	-	-	-	221..226..	218..221..	-	221..226..	218..221..	-
16000K	-	-	-	227..227..	222..224..	222..228..	227..227..	222..224..	222..228..
16000K-17000K	-	-	-	228..233..	225..228..	-	228..233..	225..228..	-
17000K	-	-	-	234..234..	229..231..	229..235..	234..234..	229..231..	229..235..
17000K-18000K	-	-	-	235..240..	232..235..	-	235..240..	232..235..	-
18000K	-	-	-	241..241..	236..239..	236..242..	241..241..	236..239..	236..242..
18000K-19000K	-	-	-	242..247..	240..243..	-	242..247..	240..243..	-
19000K	-	-	-	248..248..	244..247..	243..249..	248..248..	244..247..	243..249..
19000K-20000K	-	-	-	249..254..	248..251..	-	249..254..	248..251..	-
20000K	-	-	-	255..255..	252..255..	250..255..	255..255..	252..255..	250..255..

How to...	Settings	White 50-100-200	White 300-700	Tunable white	RGBW	6C	8C	Safey instructions	Logistics Weight & sizes
---------------------------	--------------------------	----------------------------------	-------------------------------	-------------------------------	----------------------	--------------------	--------------------	------------------------------------	--

ROSCO FILTERS CHANNEL

								White	White	TW	RGBW	6C	8C
	000	NONE	060	ROSCO R0077	120	ROSCO R4515	180	ROSCO R4730					
	001	ROSCO R0384	061	ROSCO R0075	121	ROSCO R4530	181	ROSCO R0037					
	002	ROSCO R0383	062	ROSCO R0376	122	ROSCO R4560	182	ROSCO R3308					
	003	ROSCO R0085	063	ROSCO R0071	123	ROSCO R0096	183	ROSCO R3309					
	004	ROSCO R0083	064	ROSCO R0092	124	ROSCO R0012	184	ROSCO R4715					
	005	ROSCO R0079	065	ROSCO R3316	125	ROSCO R4590	185	ROSCO R0038					
	006	ROSCO R0080	066	ROSCO R3315	126	ROSCO R0010	186	ROSCO R3313					
	007	ROSCO R2006	067	ROSCO R0087	127	ROSCO R0310	187	ROSCO R0333					
	008	ROSCO R3220	068	ROSCO R3304	128	ROSCO R0313	188	ROSCO R3314					
	009	ROSCO R2007	069	ROSCO R0088	129	ROSCO R0312	189	ROSCO R3318					
	010	ROSCO R0084	070	ROSCO R4415	130	ROSCO R0014	190	ROSCO R0351					
	011	ROSCO R0078	071	ROSCO R0388	131	ROSCO R0011	191	ROSCO R0054					
	012	ROSCO R0081	072	ROSCO R4430	132	ROSCO R2003	192	ROSCO R0051					
	013	ROSCO R0068	073	ROSCO R0086	133	ROSCO R0015	193	ROSCO R0052					
	014	ROSCO R0368	074	ROSCO R0089	134	ROSCO R3441	194	ROSCO R4915					
	015	ROSCO R0069	075	ROSCO R0389	135	ROSCO R3411	195	ROSCO R4930					
	016	ROSCO R0065	076	ROSCO R0386	136	ROSCO R0316	196	ROSCO R0356					
	017	ROSCO R0067	077	ROSCO R4460	137	ROSCO R3401	197	ROSCO R0057					
	018	ROSCO R0367	078	ROSCO R4490	138	ROSCO R3407	198	ROSCO R4960					
	019	ROSCO R0064	079	ROSCO R2004	139	ROSCO R0020	199	ROSCO R0058					
	020	ROSCO R0375	080	ROSCO R0090	140	ROSCO R2002	200	ROSCO R0357					
	021	ROSCO R0370	081	ROSCO R0091	141	ROSCO R0317	201	ROSCO R0059					
	022	ROSCO R0366	082	ROSCO R0122	142	ROSCO R0318	202	ROSCO R0336					
	023	ROSCO R0369	083	ROSCO R0126	143	ROSCO R0021	203	ROSCO R4760					
	024	ROSCO R0072	084	ROSCO R0393	144	ROSCO R0023	204	ROSCO R0044					
	025	ROSCO R0062	085	ROSCO R0094	145	ROSCO R0041	205	ROSCO R0346					
	026	ROSCO R0063	086	ROSCO R3406	146	ROSCO R0040	206	ROSCO R0349					
	027	ROSCO R0060	087	ROSCO R3405	147	ROSCO R0022	207	ROSCO R0344					
	028	ROSCO R3206	088	ROSCO R0099	148	ROSCO R0019	208	ROSCO R0039					
	029	ROSCO R0372	089	ROSCO R0017	149	ROSCO R0032	209	ROSCO R0047					
	030	ROSCO R0373	090	ROSCO R0321	150	ROSCO R4690	210	ROSCO R0348					
	031	ROSCO R3208	091	ROSCO R0018	151	ROSCO R0042	211	ROSCO R0049					
	032	ROSCO R4315	092	ROSCO R0303	152	ROSCO R0127	212	ROSCO R0048					
	033	ROSCO R3216	093	ROSCO R0030	153	ROSCO R0024	213	ROSCO R0347					
	034	ROSCO R0053	094	ROSCO R4660	154	ROSCO R0325	214	ROSCO R4990					
	035	ROSCO R3204	095	ROSCO R3310	155	ROSCO R0025	215	ROSCO R0358					
	036	ROSCO R0360	096	ROSCO R0031	156	ROSCO R2001	216	ROSCO R0056					
	037	ROSCO R4215	097	ROSCO R0034	157	ROSCO R0324	217	ROSCO R0377					
	038	ROSCO R3203	098	ROSCO R0331	158	ROSCO R0026	218	ROSCO R0385					
	039	ROSCO R0362	099	ROSCO R4630	159	ROSCO R0120	219	ROSCO R2009					
	040	ROSCO R0371	100	ROSCO R0304	160	ROSCO R0124	220	ROSCO R0353					
	041	ROSCO R0364	101	ROSCO R0003	161	ROSCO R0027	221	ROSCO R0055					
	042	ROSCO R3202	102	ROSCO R4615	162	ROSCO R0050	222	ROSCO R4230					
	043	ROSCO R3218	103	ROSCO R0305	163	ROSCO R4890	223	ROSCO R0355					
	044	ROSCO R0365	104	ROSCO R0005	164	ROSCO R0332	224	ROSCO R0378					
	045	ROSCO R0061	105	ROSCO R0016	165	ROSCO R0342	225	ROSCO R4260					
	046	ROSCO R4330	106	ROSCO R3408	166	ROSCO R0045	226	ROSCO R0359					
	047	ROSCO R0363	107	ROSCO R0009	167	ROSCO R0046	227	ROSCO R4290					
	048	ROSCO R0066	108	ROSCO R0002	168	ROSCO R0339	228	ROSCO R0082					
	049	ROSCO R0070	109	ROSCO R0013	169	ROSCO R2010	229	ROSCO R0074					
	050	ROSCO R4360	110	ROSCO R3442	170	ROSCO R4790	230	ROSCO R0381					
	051	ROSCO R4390	111	ROSCO R0008	171	ROSCO R0043	231	ROSCO R2008					
	052	ROSCO R0073	112	ROSCO R3409	172	ROSCO R343	232	ROSCO R0121					
	053	ROSCO R2005	113	ROSCO R3443	173	ROSCO R0036	233	ROSCO R0125					
	054	ROSCO R0374	114	ROSCO R0302	174	ROSCO R4860	234	ROSCO R0382					
	055	ROSCO R0093	115	ROSCO R3444	175	ROSCO R4830	235	ROSCO R0397					
	056	ROSCO R0392	116	ROSCO R3317	176	ROSCO R0035	236	ROSCO R3114					
	057	ROSCO R0095	117	ROSCO R0006	177	ROSCO R0337							
	058	ROSCO R0395	118	ROSCO R3410	178	ROSCO R4815							
	059	ROSCO R0076	119	ROSCO R0007	179	ROSCO R0033							
	CUSTOM	237	CUSTOM 1	242	CUSTOM 6	247	CUSTOM 11	252	CUSTOM 16				
		238	CUSTOM 2	243	CUSTOM 7	248	CUSTOM 12	253	CUSTOM 17				
		239	CUSTOM 3	244	CUSTOM 8	249	CUSTOM 13	254	CUSTOM 18				
		240	CUSTOM 4	245	CUSTOM 9	250	CUSTOM 14	255	CUSTOM 19				
		241	CUSTOM 5	246	CUSTOM 10	251	CUSTOM 15						

How to...	Settings	White 50-100-200	White 300-700	Tunable white	RGBW	6C	8C	Safey instructions	Logistics Weight & sizes
---------------------------	--------------------------	----------------------------------	-------------------------------	-------------------------------	----------------------	--------------------	--------------------	------------------------------------	--

LEE FILTERS CHANNEL

								White	White	TW	RGBW	6C	8C
STANDARD	000	NONE	061	LEE 131	122	LEE 232	183	LEE 787					
	001	LEE 071	062	LEE 219	123	LEE 147	184	LEE 046					
	002	LEE 713	063	LEE 241	124	LEE 776	185	LEE 113					
	003	LEE 120	064	LEE 242	125	LEE 604	186	LEE 332					
	004	LEE 363	065	LEE 728	126	LEE 207	187	LEE 748					
	005	LEE 085	066	LEE 504	127	LEE 441	188	LEE 127					
	006	LEE 119	067	LEE 730	128	LEE 204	189	LEE 148					
	007	LEE 716	068	LEE 731	129	LEE 236	190	LEE 157					
	008	LEE 195	069	LEE 213	130	LEE 744	191	LEE 192					
	009	LEE 715	070	LEE 245	131	LEE 285	192	LEE 111					
	010	LEE 723	071	LEE 733	132	LEE 013	193	LEE 036					
	011	LEE 721	072	LEE 244	133	LEE 009	194	LEE 107					
	012	LEE 722	073	LEE 138	134	LEE 205	195	LEE 110					
	013	LEE 079	074	LEE 088	135	LEE 442	196	LEE 035					
	014	LEE 714	075	LEE 505	136	LEE 764	197	LEE 247					
	015	LEE 132	076	LEE 243	137	LEE 103	198	LEE 248					
	016	LEE 068	077	LEE 121	138	LEE 206	199	LEE 249					
	017	LEE 075	078	LEE 738	139	LEE 763	200	LEE 169					
	018	LEE 197	079	LEE 122	140	LEE 443	201	LEE 136					
	019	LEE 712	080	LEE 089	141	LEE 223	202	LEE 794					
	020	LEE 525	081	LEE 139	142	LEE 279	203	LEE 170					
	021	LEE 200	082	LEE 090	143	LEE 003	204	LEE 704					
	022	LEE 719	083	LEE 736	144	LEE 444	205	LEE 052					
	023	LEE 500	084	LEE 124	145	LEE 246	206	LEE 702					
	024	LEE 366	085	LEE 735	146	LEE 007	207	LEE 137					
	025	LEE 283	086	LEE 327	147	LEE 513	208	LEE 194					
	026	LEE 174	087	LEE 740	148	LEE 514	209	LEE 058					
	027	LEE 201	088	LEE 643	149	LEE 010	210	LEE 180					
	028	LEE 281	089	LEE 642	150	LEE 100	211	LEE 701					
	029	LEE 501	090	LEE 741	151	LEE 101	212	LEE 345					
	030	LEE 708	091	LEE 746	152	LEE 767	213	LEE 703					
	031	LEE 502	092	LEE 511	153	LEE 104	214	LEE 002					
	032	LEE 503	093	LEE 653	154	LEE 765	215	LEE 795					
	033	LEE 218	094	LEE 789	155	LEE 102	216	LEE 328					
	034	LEE 278	095	LEE 512	156	LEE 550	217	LEE 048					
	035	LEE 203	096	LEE 024	157	LEE 015	218	LEE 128					
	036	LEE 202	097	LEE 025	158	LEE 768	219	LEE 793					
	037	LEE 061	098	LEE 652	159	LEE 179	220	LEE 049					
	038	LEE 063	099	LEE 017	160	LEE 770	221	LEE 126					
	039	LEE 725	100	LEE 651	161	LEE 020	222	LEE 797					
	040	LEE 117	101	LEE 134	162	LEE 286	223	LEE 798					
	041	LEE 140	102	LEE 008	163	LEE 208	224	LEE 343					
	042	LEE 353	103	LEE 779	164	LEE 742	225	LEE 700					
	043	LEE 144	104	LEE 237	165	LEE 287	226	LEE 707					
	044	LEE 724	105	LEE 747	166	LEE 105	227	LEE 181					
	045	LEE 118	106	LEE 238	167	LEE 021	228	LEE 799					
	046	LEE 172	107	LEE 176	168	LEE 158	229	LEE 508					
	047	LEE 183	108	LEE 109	169	LEE 777	230	LEE 706					
	048	LEE 141	109	LEE 790	170	LEE 778	231	LEE 199					
	049	LEE 161	110	LEE 108	171	LEE 780	232	LEE 198					
	050	LEE 196	111	LEE 773	172	LEE 022	233	LEE 710					
	051	LEE 165	112	LEE 004	173	LEE 135	234	LEE 711					
	052	LEE 352	113	LEE 152	174	LEE 507	235	LEE 142					
	053	LEE 143	114	LEE 151	175	LEE 781	236	LEE 709					
	054	LEE 727	115	LEE 153	176	LEE 019	237	LEE 053					
	055	LEE 729	116	LEE 154	177	LEE 164	238	LEE 603					
	056	LEE 116	117	LEE 506	178	LEE 182	239	LEE 602					
	057	LEE 354	118	LEE 162	179	LEE 106	240	LEE 600					
	058	LEE 115	119	LEE 650	180	LEE 029	241	LEE 601					
	059	LEE 323	120	LEE 230	181	LEE 026							
	060	LEE 322	121	LEE 156	182	LEE 027							
CUSTOM	242	CUSTOM 1	247	CUSTOM 6	252	CUSTOM 11							
	243	CUSTOM 2	248	CUSTOM 7	253	CUSTOM 12							
	244	CUSTOM 3	249	CUSTOM 8	254	CUSTOM 13							
	245	CUSTOM 4	250	CUSTOM 9	255	CUSTOM 14							
	246	CUSTOM 5	251	CUSTOM 10									
												YES	YES

How to...	Settings	White 50-100-200	White 300-700	Tunable white	RGBW	6C	8C	Safety instructions	Logistics Weight & sizes
---------------------------	--------------------------	----------------------------------	-------------------------------	-------------------------------	----------------------	--------------------	--------------------	-------------------------------------	--

MANUAL PRESET / COLOUR / CCT

	White	White	TW	RGBW	6C			8C		
					MANUAL PRESET	MANUAL COLOR	MANUAL CCT	MANUAL PRESET	MANUAL COLOR	MANUAL CCT
NONE	-	-	-	-	000..000	000..000	0..4	000..000	000..000	0..4
1500 K							5..11			5..11
1600 K							12..18			12..18
1700 K							19..25			19..25
1800 K							26..32			26..32
1900 K							33..39			33..39
2000 K							40..46			40..46
2100 K							47..53			47..53
2200 K							54..60			54..60
2300 K							61..67			61..67
2400 K							68..74			68..74
2500 K							75..81			75..81
2600 K							82..88			82..88
2700K					001..003		89..95	001..003		89..95
2800 K							96..102			96..102
2900 K							103..109			103..109
3000K					004..006		110..116	004..006		110..116
3100 K							117..123			117..123
3200K					007..009		124..130	007..009		124..130
3300 K							131..137			131..137
3400 K							138..144			138..144
3500K					010..012		145..151	010..012		145..151
4000K					013..015		152..158	013..015		152..158
5000 K							159..165			159..165
5600K					016..018		166..172	016..018		166..172
6000 K							173..179			173..179
6500K					019..021		180..186	019..021		180..186
8000K					022..024		187..193	022..024		187..193
10000 K							194..200			194..200
12000 K							201..207			201..207
14000 K							208..214			208..214
15000 K							215..221			215..221
16000 K							222..228			222..228
17000 K							229..235			229..235
18000 K							236..242			236..242
19000 K							243..249			243..249
20000 K							250..255			250..255
FULL WHITE	-	-	-	-	025..027		-	025..027		-
LEE 063	LEE 179				028..030	127..129	001..003	100..102	028..030	127..129
LEE 117	LEE 105				031..033	130..132	004..006	103..105	031..033	130..132
LEE 353	LEE 158				034..036	133..135	007..009	106..108	034..036	133..135
LEE 172	LEE 778				037..039	136..138	010..012	109..111	037..039	136..138
LEE 118	LEE 135				040..042	139..141	013..015	112..114	040..042	139..141
LEE 141	LEE 019				043..045	142..144	016..018	115..117	043..045	142..144
LEE 165	LEE 164				046..048	145..147	019..021	118..120	046..048	145..147
LEE 068	LEE 106				049..051	148..150	022..024	121..123	049..051	148..150
LEE 197	LEE 026				052..054	151..153	025..027	124..126	052..054	151..153
LEE 132	LEE 046				055..057	154..156	028..030	127..129	055..057	154..156
LEE 079	LEE 332				058..060	157..159	031..033	130..132	058..060	157..159
LEE 715	LEE 793				061..063	160..162	034..036	133..135	061..063	160..162
LEE 119	LEE 128				064..066	163..165	037..039	136..138	064..066	163..165
LEE 120	LEE 111				067..069	166..168	040..042	139..141	067..069	166..168
LEE 713	LEE 157				070..072	169..171	043..045	142..144	070..072	169..171
LEE 071	LEE 148				073..075	172..174	046..048	145..147	073..075	172..174
LEE 729	LEE 024				076..078	175..177	049..051	148..150	076..078	175..177
LEE 116	LEE 008				079..081	178..180	052..054	151..153	079..081	178..180
LEE 115	LEE 134				082..084	181..183	055..057	154..156	082..084	181..183
LEE 131	LEE 147				085..087	184..186	058..060	157..159	085..087	184..186
LEE 323	LEE 004				088..090	187..189	061..063	160..162	088..090	187..189
LEE 735	LEE 154				091..093	190..192	064..066	163..165	091..093	190..192
LEE 090	LEE 169				094..096	193..195	067..069	166..168	094..096	193..195
LEE 139	LEE 136				097..099	196..198	070..072	169..171	097..099	196..198
LEE 089	LEE 170				100..102	199..201	073..075	172..174	100..102	199..201
LEE 122	LEE 137				103..105	202..204	076..078	175..177	103..105	202..204
LEE 738	LEE 058				106..108	205..207	079..081	178..180	106..108	205..207
LEE 088	LEE 180				109..111	208..210	082..084	181..183	109..111	208..210
LEE 138	LEE 126				112..114	211..213	085..087	184..186	112..114	211..213
LEE 100	LEE 797				115..117	214..216	088..090	187..189	115..117	214..216
LEE 010	LEE 798				118..120	217..219	091..093	190..192	118..120	217..219
LEE 101	LEE 707				121..123	220..222	094..096	193..195	121..123	220..222
LEE 104	LEE 181				124..126	223..225	097..099	196..198	124..126	223..225
CUSTOM 1	CUSTOM 11				226..228	199..201	229..231		226..228	199..201
CUSTOM 2	CUSTOM 12				229..231	202..204	232..234		229..231	202..204
CUSTOM 3	CUSTOM 13				232..234	205..207	235..237		232..234	205..207
CUSTOM 4	CUSTOM 14				235..237	208..210	238..240		235..237	208..210
CUSTOM 5	CUSTOM 15				238..240	211..213	241..243		238..240	211..213
CUSTOM 6	CUSTOM 16				241..243	214..216	244..246		241..243	214..216
CUSTOM 7	CUSTOM 17				244..246	217..219	247..249		244..246	217..219
CUSTOM 8	CUSTOM 18				247..249	220..222	250..252		247..249	220..222
CUSTOM 9	CUSTOM 19				250..252	223..225	253..255		250..252	223..225
CUSTOM 10					253..255	226..228		253..255	226..228	253..255

How to...	Settings	White 50-100-200	White 300-700	Tunable white	RGBW	6C	8C	Safety instructions	Logistics Weight & sizes
---------------------------	--------------------------	----------------------------------	-------------------------------	-------------------------------	----------------------	--------------------	--------------------	-------------------------------------	--

DELAY CHANNEL

	White	White	TW	RGBW	6C	8C
DELAY	-	YES	YES	YES	YES	YES
0..45	NONE (The LED delay follows the set on the menu display)					
46..55	0 ms					
56..65	50 ms					
66..75	100 ms					
76..85	150 ms					
86..95	200 ms					
96..105	240 ms					
106..115	300 ms					
116..125	350 ms					
126..135	400 ms					
136..145	450 ms					
146..155	500 ms					
156..165	330 ms					
166..175	600 ms					
176..185	800 ms					
186..195	900 ms					
196..205	1000 ms					
206..215	1200 ms					
216..225	1400 ms					
226..235	1600 ms					
236..245	1800 ms					
246..255	2000 ms					

RDM (Remote Device Management)

Questa sezione riporta i valori che possono essere interrogati da remoto attraverso consolle RDM.

Plasa/ESTA Denomination	Number of Channels
DEVICE_INFO	Reading of the following parameters: - RDM protocol version - Device Model ID - Product category - ID version sw - Number of DMX channels - DMX mode index - DMX address - Number of sub-devices - Number of sensors
IDENTIFY_DEVICE	LED power on - allowing fixture identification
DMX_START_ADDRESS	DMX address setting/reading
SOFTWARE_VERSION_LABEL	Text description version sw
SUPPORTED_PARAMETERS	List of supported parameters
DMX_PERSONALITY	DMX mode setting
DMX_PERSONALITY_DESCRIPTION	Obtaining textual description of DMX mode
DEVICE_MODEL_DESCRIPTION	Text description of the device model
MANUFACTURER_LABEL	Text description manufacturer
SENSOR_DEFINITION	Display of the values read by the temperature sensor, expressed in tenths of Celsius degree
SENSOR_VALUE	

Error list

Errore message	What does it mean?	White	White	TW	RGBW	6C	8C
LED NTC SENSOR ERROR	Non corretto funzionamento del sensore NTC LED						
LED NTC OVERTEMPERAURE	Superamento della temperatura di lavoro del sensore NTC LED						
MICRO NTC SENSOR ERROR	Non corretto funzionamento del sensore NTC MICRO						
MICRO NTC OVERTEMPERAURE	Superamento della temperatura di lavoro del sensore NTC MICRO						
DRIVER1 NTC SENSOR ERROR	Non corretto funzionamento del sensore NTC DRIVER1						
DRIVER1 NTC VERTEMPERAURE	Superamento della temperatura di lavoro del sensore NTC DRIVER1						
DRIVER2 NTC SENSOR ERROR	Non corretto funzionamento del sensore NTC DRIVER2						
DRIVER2 NTC VERTEMPERAURE	Superamento della temperatura di lavoro del sensore NTC DRIVER2						
LOW SUPPLY VOLTAGE	La tensione di alimentazione misurata è sotto la soglia						
HIGH SUPPLY VOLTAGE	La tensione di alimentazione misurata è sopra la soglia						
OUT LED1 ERROR	Non corretto funzionamento della catena LED OUT 1						
OUT LED.. ERROR	Non corretto funzionamento della catena LED OUT ..						
OUT LED8 ERROR	Non corretto funzionamento della catena LED OUT 8						
ENCODER BUS ERROR	Errore di comunicazione con scheda Encoder						

How to...	Settings	White 50-100-200	White 300-700	Tunable white	RGBW	6C	8C	Safety instructions	Logistics Weight & sizes
---------------------------	--------------------------	----------------------------------	-------------------------------	-------------------------------	----------------------	--------------------	--------------------	-------------------------------------	--

How to

In questa sezione sono riportate le principali necessità di un operatore luci e come settare le singole funzioni dei fari.

HOW TO SET DMX ADDRESS AND TO CHOOSE DMX PERSONALITY (DMX CHART)

In order to control one or more fixtures via console, it is necessary to assign each one a DMX address and choose a DMX chart based on the parameters of the luminaire you want to control and the channels available on the console. At the first fixture, channel 1 is allocated and occupies as many channels as indicated in the chosen DMX chart.

[DMX SETTINGS => DMX ADDRESS = 001](#)

[DMX SETTINGS => DMX PERSONALITY = 3ch \(example\)](#)

If the second fixture is given the same channel and the same personality, it will behave like the first luminaire; otherwise it is necessary to give it the first free channel as an address and choose how to work it.

[DMX SETTINGS => DMX ADDRESS = 004](#)

[DMX SETTINGS => DMX PERSONALITY = xxx](#)

HOW TO EMULATE THE PERFORMANCE OF HALOGEN LAMP

To satisfy the most "nostalgic" light designers of halogen light and to approach the natural perception that the human eye has of an LED illuminated object, it is not enough that static light simulates halogen light, but that it is also in its dynamic regulation.

For an LED luminaire to behave like a halogen lamp 3 are the points to consider:

- the **dimmer curve** must be set as HALO
[OPTIONS → AMBER SHIFT = ON](#)
- the **delay** should be adjusted to 1000 ms
[OPTIONS → LED DELAY = 1000ms](#)
- the **amber shift** function must be activated (typical change to which an halogen lamp tends when dimmed decreasing the emission)
[OPTIONS → DIMMING CURVE = HALO](#)
- mandatory: [DMX PERSONALITY / CCT PRESET = 3200K](#)

HOW TO INCREASE THE LIGHT OUTPUT +20%

All the fixtures are designed to work in a context of balance between luminous efficiency and optimal thermal regime so as not to cause the LED to work under stress. Where available, thanks to the LED BOOST function, the algorithm favors luminous efficiency (+20% in light output) to the detriment of thermal efficiency, giving more current to the LED, but it is exclusively compatible with FAN MODE = AUTO (= the fans are automatically adjusted based on the LED temperature). That means that, even with this function active, the LED TEMPERATURE function regulates the light intensity in case of overtemperature to avoid an early deterioration of the source.

It may happen that you need a light emission of the individual channels higher than the factory settings, without however exceeding the maximum power of the spotlight. When a tint or a CCT value is selected in which not all channels are at full, an algorithm increases the light output to achieve maximum efficiency. A microprocessor monitors the working temperature of the LED and updates the source control parameters in real time.

[OPTIONS -> FAN MODE = AUTO](#)

[OPTIONS -> LED BOOST = ON](#)

HOW TO SET THE FAN MODE

In order to function properly, the LED requires a cooling system, which can be passive (dissipation of heat by natural convection) or active (forced dissipation of heat using a fan).

FAN MODE:

- AUTO: the fans are automatically adjusted based on the LED temperature.(where variable fan noise is not a critical parameter)
- STANDARD: the fans are always kept at the default value (where a constant background noise is required without varying brightness)
- SILENT: the fans are always kept at the minimum value and in case of critical temperatures of the LED it automatically reduces the brightness

The **silent mode** function allows to intervene on the speed and therefore on the noise of the fans based on the internal temperatures of work detected by a thermostat

[OPTIONS → FAN MODE = SILENT](#)

HOW TO SET THE DISPLAY

To avoid unwanted light emission of the display you can turn it off.

[OPTIONS → DISPLAY = OFF](#)

If the fixture is mounted "upside down" it is also possible to rotate the display to make it easier to read.

[OPTIONS → DISPLAY ROTATION = ROTATED](#)

How to...	Settings	White 50-100-200	White 300-700	Tunable white	RGBW	6C	8C	Safety instructions	Logistics Weight & sizes
---------------------------	--------------------------	----------------------------------	-------------------------------	-------------------------------	----------------------	--------------------	--------------------	-------------------------------------	--

HOW TO REMOVE FLICKERING EFFECT IN CAMERAS

The flickering effect is manifested in the shooting when the emission frequency of the LED conflicts with the camera brush scan and can be solved by acting on the camera parameters or on the fixture parameters.

[OPTIONS → OUTPUT FREQUENCY = xxx](#) (find by trial and error - fine adjustment - the value that removes the flicker in the camera)

HOW TO HOW TO CALIBRATE LED COLORS

When using a group of fixtures it may happen that one or more of them, with the same DMX values, has a color component (eg: red) to be corrected to align the tint to the other luminaires. Simply enter the fixture menu and adjust the DMX value until the tint aligns with that of the other luminaires of the group.

[LED CALIBRATION → RED CALIBRATION](#)

HOW TO SET THE COLOUR CUSTOM PRESETS

In each color Hyperion series fixture there are two libraries:

- the first factory ([STANDARD PRESETS](#)) and
- the second customizable by the operator ([CUSTOM PRESETS](#)) which includes a storage phase and a playback. Both of these presets can be recalled by selecting the relevant DMX value or by turning the potentiometer

There are two ways to customize the CUSTOM PRESET:

with fixture display:

- [SETTINGS → STAND ALONE → CUSTOM PRESETS → CUSTOM PRESET 1](#)
- set the desired color by changing the values of the individual colors by turning the dimmer
- click on the CONFIRM button for the final save
- wait 5 seconds and the 5 flashes confirming that saving has taken place

with DMX console:

- modify the DMX value of the [SERVICE 1](#) channel until reaching the range of the parameter to be modified (e.g. CUSTOM PRESET 1) and leave the channel on this value
- set the desired tint by acting on the individual color channels
- save the tint by setting the DMX value of the [STROBE & STORE](#) channel in the range corresponding to STORE 1
- wait 5 seconds and the 5 flashes confirming that saving has taken place

FUNZIONI AVANZATE SULLA GESTIONE DEL COLORE

- Plus/Minus Green** – si tratta di una funzione che consente una regolazione fine della componente verde del CCT selezionato per adeguarlo alle specifiche esigenze dell'applicazione.
- Bilanciamento automatico** del colore durante l'intera dimmerazione per mantenere la stessa tinta quando diminuisce l'emissione di luce; l'algoritmo consente di:
 - mantenere fissa la lunghezza d'onda di ogni singolo chip LED colorato
 - mantenere costante il rapporto delle emissioni luminose tra i LED di diverso colore al variare dell'emissione luminosa
- Booster**
- Calibrazione**

How to...	Settings	White 50-100-200	White 300-700	Tunable white	RGBW	6C	8C	Safety instructions	Logistics Weight & sizes
---------------------------	--------------------------	----------------------------------	-------------------------------	-------------------------------	----------------------	--------------------	--------------------	-------------------------------------	--

HOW TO SET STAND-ALONE AND MASTER-SLAVE FUNCTIONS

May happen the need to control one or more fixtures without using a console. The software allows you to create one or more static colors and define the duration and sequence of each.

- to create a single static tint
[STANDALONE => STANDALONE = MANUAL](#)
- create multiple static colors with customizable duration and sequence
[STANDALONE => STANDALONE = AUTO SCENE](#)

The function can be set on a single fixture or on a group of fixtures. In this second case it is necessary to define the headlight "master" (MASTER, MANUAL or AUTO SCENE) and the headlights "slave" (SLAVE).

To disable these control modes in the absence of consoles simply reconnect the DMX cable and the fixtures will be controllable directly from remote. Tutto questo può riguardare un singolo faro (STAND ALONE) oppure un gruppo di fari nel quale è necessario però definire il faro "master" (MASTER) e i fari "slave" (SLAVE).

- DISABLED: The luminaire is controlled by the DMX input and by the potentiometer.
- STDALONE MANUAL: The luminaire ignores the DMX signal and the potentiometer. The colour can be set from the [STANDALONE → MANUAL MODE](#)
- STDALONE AUTO SCENE: The luminaire ignores the DMX signal and the potentiometer and performs the memorised scenes sequence (max 10 scenes) selectable from the [STANDALONE → AUTO SCENE MODE](#)
- MASTER MANUAL: The luminaire ignores the DMX signal, turns to a fix colour selectable from the [STANDALONE → MANUAL MODE](#)
Being MASTER the luminaire sends via DMX the command to control the SLAVE luminaires connected in line
- MASTER AUTO SCENE: The luminaire ignores the DMX signal and the potentiometer and performs the memorised scenes sequence (max 10 scenes) selectable from the [STANDALONE → AUTO SCENE MODE](#)
Being MASTER the luminaire sends via DMX the command to control the SLAVE luminaires connected in line
- SLAVE: The luminaire ignores the DMX signal and the potentiometer, and follows the MASTER luminaire via DMX line.

MANUAL MODE	AUTO SCENE MODE	CUSTOM PRESETS																																																																									
<p>Push UP or DOWN to select which item to edit (RED, GREEN...) Press ENTER to proceed with the editing: the value next to the item lights up. Use the dimmer potentiometer to edit the value Press ENTER to confirm the editing, ESC to go back Once all the desired items are edited: - move to CONFIRM and press ENTER to confirm or move to ABORT and press ENTER to cancel the changes - press ESC on any entry to exit without saving the changes</p> <table border="1"> <tr> <td>MANUAL</td> <td></td> <td></td> </tr> <tr> <td>RED 000</td> <td>AMB 000</td> <td></td> </tr> <tr> <td>GRN 000</td> <td>CYA 000</td> <td></td> </tr> <tr> <td>BLU 000</td> <td>LIM 000</td> <td></td> </tr> <tr> <td>ABORT</td> <td>CONFIRM</td> <td></td> </tr> </table>	MANUAL			RED 000	AMB 000		GRN 000	CYA 000		BLU 000	LIM 000		ABORT	CONFIRM		<p>Push UP or DOWN to select which item to edit (RED, GREEN..). Press ENTER to proceed with the editing: the value next to the item lights up. Use the dimmer potentiometer to edit the value Press ENTER to confirm the editing, ESC to go back Once all the desired items are edited: - move to CONFIRM and press ENTER to confirm or move to ABORT and press ENTER to cancel the changes - press ESC on any entry to exit without saving the changes</p> <table border="1"> <tr> <td>SCENE X</td> <td></td> <td></td> </tr> <tr> <td>RED 000</td> <td>AMB 000</td> <td></td> </tr> <tr> <td>GRN 000</td> <td>CYA 000</td> <td></td> </tr> <tr> <td>BLU 000</td> <td>LIM 000</td> <td></td> </tr> <tr> <td>ABORT</td> <td>CONFIRM</td> <td></td> </tr> </table>	SCENE X			RED 000	AMB 000		GRN 000	CYA 000		BLU 000	LIM 000		ABORT	CONFIRM		<p>Push UP or DOWN to select which item to edit (RED, GREEN..). Press ENTER to proceed with the editing: the value next to the item lights up. Use the dimmer potentiometer to edit the value Press ENTER to confirm the editing, ESC to go back Once all the desired items are edited: - move to CONFIRM and press ENTER to confirm or move to ABORT and press ENTER to cancel the changes - press ESC on any entry to exit without saving the changes</p> <table border="1"> <tr> <td>CUSTOM PRESET X</td> <td></td> <td></td> </tr> <tr> <td>RED 000</td> <td>AMB 000</td> <td></td> </tr> <tr> <td>GRN 000</td> <td>CYA 000</td> <td></td> </tr> <tr> <td>BLU 000</td> <td>LIM 000</td> <td></td> </tr> <tr> <td>ABORT</td> <td>CONFIRM</td> <td></td> </tr> </table> <p>Item Value Def Description</p> <table border="1"> <tr> <td>SCENE SET</td> <td></td> <td></td> <td>You enter in the scene setting screen, described in the relevant paragraph.</td> </tr> <tr> <td>PAUSE TIME</td> <td>0.1 .. 60.0 s</td> <td>1.0 s</td> <td>It is the duration time of the scene</td> </tr> <tr> <td>FADE TIME</td> <td>0.1 .. 60.0 s</td> <td>1.0 s</td> <td>It is the fading time towards the next scene</td> </tr> <tr> <td>SCENE DELETE</td> <td>Enter to Delete Esc to Exit</td> <td></td> <td>Deleting of the scene</td> </tr> <tr> <td>FROM DMX</td> <td>Enter to Copy from Dmx Esc to Exit</td> <td></td> <td>Copy of the scene from Dmx signal: press Enter to see the set scene through Dmx and press Enter again to confirm the copy. In case of DMX absence, "Dmx Not Present" will be displayed</td> </tr> <tr> <td>SCENE COPY</td> <td>Enter to Copy Esc to Exit</td> <td></td> <td>COPY of the scene: the scene (RGBACL values + pause time and Fade) is copied in the memory so to be pasted later</td> </tr> <tr> <td>SCENE PASTE</td> <td>Enter to Paste Esc to Exit</td> <td></td> <td>PASTE the scene: the scene previously copied is pasted on the activescene.</td> </tr> </table>	CUSTOM PRESET X			RED 000	AMB 000		GRN 000	CYA 000		BLU 000	LIM 000		ABORT	CONFIRM		SCENE SET			You enter in the scene setting screen, described in the relevant paragraph.	PAUSE TIME	0.1 .. 60.0 s	1.0 s	It is the duration time of the scene	FADE TIME	0.1 .. 60.0 s	1.0 s	It is the fading time towards the next scene	SCENE DELETE	Enter to Delete Esc to Exit		Deleting of the scene	FROM DMX	Enter to Copy from Dmx Esc to Exit		Copy of the scene from Dmx signal: press Enter to see the set scene through Dmx and press Enter again to confirm the copy. In case of DMX absence, "Dmx Not Present" will be displayed	SCENE COPY	Enter to Copy Esc to Exit		COPY of the scene: the scene (RGBACL values + pause time and Fade) is copied in the memory so to be pasted later	SCENE PASTE	Enter to Paste Esc to Exit		PASTE the scene: the scene previously copied is pasted on the activescene.
MANUAL																																																																											
RED 000	AMB 000																																																																										
GRN 000	CYA 000																																																																										
BLU 000	LIM 000																																																																										
ABORT	CONFIRM																																																																										
SCENE X																																																																											
RED 000	AMB 000																																																																										
GRN 000	CYA 000																																																																										
BLU 000	LIM 000																																																																										
ABORT	CONFIRM																																																																										
CUSTOM PRESET X																																																																											
RED 000	AMB 000																																																																										
GRN 000	CYA 000																																																																										
BLU 000	LIM 000																																																																										
ABORT	CONFIRM																																																																										
SCENE SET			You enter in the scene setting screen, described in the relevant paragraph.																																																																								
PAUSE TIME	0.1 .. 60.0 s	1.0 s	It is the duration time of the scene																																																																								
FADE TIME	0.1 .. 60.0 s	1.0 s	It is the fading time towards the next scene																																																																								
SCENE DELETE	Enter to Delete Esc to Exit		Deleting of the scene																																																																								
FROM DMX	Enter to Copy from Dmx Esc to Exit		Copy of the scene from Dmx signal: press Enter to see the set scene through Dmx and press Enter again to confirm the copy. In case of DMX absence, "Dmx Not Present" will be displayed																																																																								
SCENE COPY	Enter to Copy Esc to Exit		COPY of the scene: the scene (RGBACL values + pause time and Fade) is copied in the memory so to be pasted later																																																																								
SCENE PASTE	Enter to Paste Esc to Exit		PASTE the scene: the scene previously copied is pasted on the activescene.																																																																								
		<p>Read How to set the colour custom presets</p>																																																																									

How to...	Settings	White 50-100-200	White 300-700	Tunable white	RGBW	6C	8C	Safety instructions	Logistics Weight & sizes
---------------------------	--------------------------	----------------------------------	-------------------------------	-------------------------------	----------------------	--------------------	--------------------	-------------------------------------	---

Safety instructions

This manual contains all the safety information required for the appropriate use of the fixture. It shall be carefully read it and stored for future requirements.

Spotlight sc will not be responsible for any damage to the fixture itself, to other objects or people due to improper installation or use of the fixture either than hereinafter specified. Additionally, you are required to download the User Manual from www.spotlight.it for a comprehensive knowledge al each and all functions.

UNPACKING

Remove the fixture from its package and make sure no damage incurred during transport. In the event of damages, a report or claim shall be issued to the transport agent and the seller to start the repair or replacement process.

PRINTED NOTES ON THE FIXTURES

A label of the fixture' side displays the following information:

- Model part number
- Mains a.c.~ voltage (V)
- Power (W)
- Frequency (Hz)
- Protection rate (IP 20)
- t_a max: maximum ambient temperature allowed ($^{\circ}$ C)
- t max: external surface temperature at thermal regime ($^{\circ}$ C)
- X m minimum recommended distance between the fixture and the lighted object (m)
-  Risk Group 2, in compliance with EN62471. Do not face directly the light source as it might damage your eyesight.
-  Photo-Biological safety: do not stare at the light source while functioning
-  Dispose of waste: in compliance to 2012/19/EU, this fixture shall be disposed according to proper waste-class regulation

INSTALLATION

- This fixture is designed only for professional use, not for domestic use or handling
- This fixture can be either hung from top or fitted onto a tripod
- Make sure the hanging point is safe and stable. Additionally add a safety rope if required by local safety regulation
- Do not focus the light beam straight onto somebody's eyes

ELECTRICAL CONNECTION

Electrical wiring, plugging and cabling shall be made by professional or qualified technicians. Before and during installation, attend to the following procedures:

- Check that Mains Voltage and Frequency comply with what printed on the fixture's label
- Always check the Mains line is properly grounded
- Check the working power of the fixture, as printed on its label, to prevent from line overload
- This fixtures is foreseen for indoor use: it shall be protected from rain and humidity if used under different conditions (IP 20)

MAINTENANCE

Do not open the fixture before disconnecting from the mains: an electrical shock might occur. A complete inspection shall be made once a year to check the electrical and mechanical parts' integrity and the software upgrades. Repairs shall be made by the manufacturer only or its appointed after-sale service center. After cleaning, the lenses shall be re-assembled and, if scratched or ruined, they shall be replaced with original parts.

COMPLIANCE

This products complies with the European Directives:

- 2014/35/EU: Safety on Low Voltage Directive LVD
- 2014/30/EU: Electromagnetic Compatibility EMC
- 2011/65/EU: Restriction of Hazardous Substances Directive RoHS



How to...	Settings	White 50-100-200	White 300-700	Tunable white	RGBW	6C	8C	Safey instructions	Logistics Weight & sizes
---------------------------	--------------------------	----------------------------------	-------------------------------	-------------------------------	----------------------	--------------------	--------------------	------------------------------------	--

Logistics

Nella seguente tabella sono riportati i pesi e gli ingombri dei fari e dei relativi imballi.

		Fixture						Packing			HS Code	
Power	Type	Code	Weight (kg)	Dimensions (cm)			Weight (kg)	Dimensions (cm)			HS Code	
				Length	Width	Height		Length	Width	Height		
50W	Fresnel	FN LED 50 CW / WW	3	25	16	27	3,5	40	22	22	94054210	
		FN LED 50 RGBW		29				51	26	26		
	PC	PC LED 50 CW / WW	4	5	5	5	5	10	0,4	10	94059900	
	Profile	PR LED 50 ZS WW / RGBW		15,3				15,3	6,7	5		
	Accessories	TC MINI	0,1	10	0,4	10	0,1	10	0,4	10	94059900	
		PL 4 MIN	0,4	15,5	11,5	3,3	0,5	18	13	4,4		
		PGM MIZO	0,1	15,3	6,7	5	0,1	15,3	6,7	5		
100W	Fresnel	FN HY LED 100 CW / WW	3,5	31	22	29	4,1	38,5	22,5	18,5	94054210	
	PC	PC HY LED 100 CW / WW	6,2	54	34	40	7,6	57	27,5	27,5		
	Profile	PR HY LED 100 ZS CW / WW		6								
	Accessories	PR HY LED 100 ZW CW / WW	6	45	10	0,5	7,4	21	10	0,5	94059900	
		TC S05	0,1	14	0,4	14	0,1	14	0,4	14		
		PL 4 U05	0,8	22,5	17	3,5	0,9	24,5	19	5,5		
		DIA 05	0,3	8,5	10,5	2,5	0,3	21	13	5		
200W	Accessories	PGB R 100	0,1	21	10	0,5	0,1	10	0,5	0,5	94059900	
		FN HY LED 200 CW / WW	6	36	30	35	6,7	46,5	31,5	38		
		FN HY LED 200 TW / RGBW / 6C	7,5	45		39	8,7					
		PC HY LED 200 CW / WW	6	36		35	6,7					
	Profile	PC HY LED 200 TW / RGBW / 6C	7,5	45	34	39	8,7	12,5	82	34	37	
		PR HY LED 200 ZS CW / WW / TW / RGBW / 6C	11,5	76		47	13,5	92	36	40		
		PR HY LED 200 ZW CW / WW / TW / RGBW / 6C	11	64		47	12,5	82	34	37		
300W	Accessories	TC HY 200	0,1	18,5	0,4	18,5	0,1	18,5	0,4	18,5	94059900	
		PL 4 HY 200	1	28,5	21	4	1,1	34	23	5,5		
		DIA HY	0,2	21,7	12	1,3	0,3	25	18	1,5		
		PGB HY	0,1	24	9,5	0,4	0,1	24	9,5	0,4		
	Profile	PR HY OP ZS	6,2	48	25,5	23	7,6	71	36	40	94054210	
		PR HY OP ZW	5,2	36		23	6,5	46,5	31,5	38		
		FN HY LED 300 CW / WW / TW / 6C	9,5	48	30	43	10,9	71	36	40		
700W	PC	PC HY LED 300 CW / WW / TW / 6C	12,5	57	34	47	13,5	92	40	40	94054210	
	Profile	PR HY LED 300 ZS CW / WW / TW / 6C	15	76		47	18,5					
		PR HY LED 300 ZW CW / WW / TW / 6C	14	64		47	18					
	Followspot	FS HY LED 300 CW	19	100	35	35	22	115	40	94059900		
	Cyclorama	CYC LED 300 RGBW	15	57	43	25	18,2	61	57	33		
	Accessories	TC S25	0,3	25	0,4	25	0,3	25	0,4	25		
		PL 4 U25	1,7	38	27	3,5	1,7	42	29	5,5		
		PL 8 U25	2									
700W	Fresnel	FN HY LED 700 CW / WW / TW / 8C	18	60	40	50	42	40	40	94054210		
	PC	PC HY LED 700 CW / WW / TW / 8C	20	69		47						
	Profile	PR HY LED 700 ZS CW / WW / TW / 8C	31	127		47						
		PR HY LED 700 ZW CW / WW / TW / 8C	28	92		47						
	Followspot	FS HY LED 700 CW	36	144		42						
	Accessories	TC HY 700	0,4	30	30	0,4	0,4	30	30	0,4	94059900	
		PL 4 HY 700										
		DIA HY 700										
		PGB HY 700										